

Wikiprint Book

Title: Documentation/ARexxAPI/APPBUSY

Subject: YAM - Yet Another Mailer - Documentation/ARexxAPI/APPBUSY

Version: 6

Date: 31.01.2015 15:48:45

Table of Contents

Languages:	3
APPBUSY	3

Languages:

- **English**
- [Español](#)

APPBUSY

NAME

AppBusy -- Switch YAM into busy state. (V2.0)

TEMPLATE

TEXT

FUNCTION

Switches YAM into busy state and optionally displays a short text in the status bar. During this state, YAM won't accept any input.

INPUTS

TEXT - optional, a brief piece of text to display in the status bar while YAM is in busy state; the maximum length of the displayable text depends on the width of the characters used

RETURNS

RC is set to 1 if YAM was already busy.

NOTES

V2.4 introduced the concept of busy levels, meaning the command is now accumulative: if AppBusy is called several times, an equal number of calls to AppNoBusy must be made for the application to return to normal state.

EXAMPLE

```
/* Turn busy mode on */
'APPBUSY "Please wait..."

/* Say we are doing something different */
'APPBUSY "Making coffee..."

/* Turn all busy modes off */
APPNOBUSY
APPNOBUSY
```

BUGS

SEE ALSO

[APPNOBUSY](#)